



| audio manufaktur |

*no sound / just music*

## Torus Power

### RM-Serie

#### SPECIFICATIONS

CE RM SERIES					
	RM 4 CE	RM 8 CE	RM 16 CE	RM 30 CE	RM 45 CE
<b>FACEPLATE</b>	19" RACK MOUNT (RK), 17" SILVER (CS), 17" BLACK (CB)				
<b>CHASSIS</b>	2U	3U	4U	4U	5U
<b>INPUT V</b>	220 – 240 VAC				
<b>OUTPUT VOLTS</b>	220 – 240 VAC				
<b>INPUT CURRENT LIMITING *</b>	4A (C)	8A (C)	16A (C)	2 X 30A (F)	2 X 45A (F)
<b>OUTPUT CURRENT</b>	4A	8A	16A	30A	45A
<b>POWER VA</b>	960	1,920	3,840	7,200	10,800
<b>FREQUENCY</b>	50 / 60 Hz				
<b>NO. OUTLETS</b>	4	5	8	8	12
<b>INLET TYPE 250V</b>	IEC 15A		IEC 20A	TWIST LOCK 30A	TWIST LOCK 50A
<b>OUTLET TYPE 250V</b>	SCHUKO CEE7, 16A				
<b>WEIGHT LB</b>	38.5	75	119	172	216
<b>WEIGHT KG</b>	17.5	34	54	78	98
<b>SIZE MM</b>					
<b>W **</b>	483	483	483		483
<b>D</b>	287	419	483		559
<b>H</b>	102	159	203		249
<b>SIZE IN</b>					
<b>W **</b>	19	19	19	19	19
<b>D</b>	11.3	16.5	19	19	22
<b>H</b>	4	6.3	8	8	9.8

\* (F) – Fuse(s) (C) – Circuit Breaker

\*\* Width (W) is based on RACK MOUNT (RK) Faceplate